

CPPY series Programming


- 1) PC system should be Win 7 or higher; .NETFramework 4.8
- 2) Connect mini-USB to the PG-3200 and connect both USB A connectors to USB ports on the PC. If using a USB hub, make sure it is self-powered.



- 3) The power LED will illuminate.



- 4) Launch software (Box connected message, see 1 below).
- 5) Place device in appropriate socket
- 6) Select tab CPPY
- 7) Enter required frequency, see 2 below
- 8) Select required supply voltage from dropdown, see 3 below
- 9) Select Calculate button, see 4 below then Program, see 5 below



The photo below shows the connections for the ZIF socket.

